## SIEMENS

## Data sheet

## 6ES7132-4BD02-0AA0



SIMATIC DP, 5 electronic modules for ET 200S, 4 DO standard 24 V DC/0.5 A, 15 mm width, 5 units per packing unit

Supply voltage	
Reverse voltage protection	Yes; when using the same load voltage as on the power module
Load voltage L+	res, when using the same load voltage as on the power module
Rated value (DC)	24 V; From power module
Reverse polarity protection	Yes; polarity reversal can lead to the digital outputs being connected through
input current	res, polarity reversal car read to the digital outputs being connected through
from load voltage L+ (without load), max.	10 mA; Per channel
from backplane bus 3.3 V DC, max.	10 mA
Power loss	
Power loss, typ.	0.8 W
Address area	
Address space per module	
Address space per module, max.	1 byte
with packing	4 bit
Digital outputs	
Type of digital output	Source output (PNP, current-sourcing)
Number of digital outputs	4
Short-circuit protection	Yes
<ul> <li>Response threshold, typ.</li> </ul>	1 to 1.5 A
Limitation of inductive shutdown voltage to	L+ (-55 to -60 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
<ul> <li>on lamp load, max.</li> </ul>	5 W
Load resistance range	
lower limit	48 Ω
upper limit	3 400 Ω
Output voltage	
<ul> <li>for signal "1", min.</li> </ul>	L+ (-1 V)
Output current	
<ul> <li>for signal "1" rated value</li> </ul>	0.5 A
<ul> <li>for signal "1" permissible range, min.</li> </ul>	7 mA
<ul> <li>for signal "1" permissible range, max.</li> </ul>	600 mA
<ul> <li>for signal "0" residual current, max.</li> </ul>	0.3 mA
Output delay with resistive load	
• "0" to "1", max.	50 µs
• "1" to "0", max.	120 µs
Parallel switching of two outputs	
for uprating	No
<ul> <li>for redundant control of a load</li> </ul>	Yes; per module
Switching frequency	

800 Hz
2 Hz
10 Hz
2 A
1 000 m
600 m
No
Yes
1 byte
No
Yes
500 V DC
15 mm
81 mm
52 mm
40 g

last modified:

9/22/2023 🖸