




## Replacement Lamps

**Table 32 - Pilot Lights, Illuminated Push Buttons, Illuminated Push-Pull, Illuminated Push-Pull/Twist to Release, and Illuminated Selector Switches**

Lamp	Type	Current, Typical	Lamp Voltage	ANSI No.	Catalog Voltage Code	Cat. No.
 Incandescent	Full-voltage Transformer	150 mA/250 mA	6.3V AC	755/1866	6, 16, 26, 36, 46, 56, 76	800T-N65 <sup>(1)</sup>
	Full Voltage	80 mA	14V AC/DC	756	12	800T-N141 <sup>(1)</sup>
		70 mA	24V AC/DC	757	24	800T-N157 <sup>(1)</sup>
		50 mA	48V AC/DC	1835	48	800T-N365 <sup>(1)</sup>
	Full-voltage Resistor	22 mA	120V AC/DC	949	10, 11	800T-N169 <sup>(1)</sup>
	Flashing	150 mA	6V AC/DC	267	6	800T-N212 <sup>(1)</sup>
Dual-input Diode	57 mA	24V AC/DC	24 MB	24	800T-N180 <sup>(1)</sup>	
	21 mA	120V AC	90 MB	16	800T-N261 <sup>(1)</sup>	
 Neon	—	2 mA	120V AC/DC	B2A	10, 20	609-N9
Lamp	Type	Current, Typical	Lamp Voltage	Leakage Current	Code	Cat. No. <sup>(2)</sup>
 LED	Universal	13 mA @ 24V DC 8.5 mA @ 120V AC <sup>(3)</sup>	3V <sup>(4)</sup>	3 mA	2	800T-N376x <sup>(5)</sup>
	Transformer	60	6V	14 mA	16, 26, 46, 56	800T-N377x <sup>(5)</sup>

(1) Item is sold in multiples of five. Order quantity of five to receive package of five pieces.


(2) To complete the cat. no. replace the x with the first letter of the desired color: Green, Red, or White.

(3) Typical current consumption values that are indicated are relative to the input of the power module.

(4) Lamp is intended for use with power module Cat. No. 800TC-N374, which has an input voltage rating of 12 ...130V AC/DC.

(5) Lamp useful lifetime is 50,000 hours (L70 classification – light output will have diminished 70% at 50,000 hours).

**Table 33 - Legacy LED Lamps**

Lamp	Type	Current, Typical	Lamp Voltage	Leakage Current	Catalog Voltage Code	Cat. No. <sup>(1) (2)</sup>
 LED <sup>(3)</sup>	Full Voltage	16 mA	24...48V AC/DC	3 mA	24, 32, 48	800T-N419x
		12 mA	120...130V AC/DC	3 mA	10, 13	800T-N421x
	Flashing <sup>(4)</sup>	18 mA	24V AC/DC	—	—	800T-N319Fx


(1) In full-voltage applications, these lamps are intended to be used with power module Cat. No. 800T-N330.

(2) To complete the cat. no. replace the x with the first letter of the desired color: Green, Red, or White.

(3) All LEDs have an internal shunt resistor for use with solid-state outputs. LEDs do not illuminate below the listed leakage current.

(4) Flashing rate is 2 Hz.

**Table 34 - Cluster Pilot Lights**

Lamp	Type	Current, Typical	Lamp Voltage	Polarity	Cat. No.
 LED	Full Voltage	15 mA	12V AC/DC	Bi-polar	800T-N341W <sup>(1)</sup>
			28V AC/DC		800T-N80W <sup>(2)</sup>

(1) Can also be used for replacement in transformer type and 6V full voltage cluster pilot light units.

(2) For use with 24V AC/DC rated devices.