## SIEMENS

## Product data sheet

3-PHASE INFEED TERMINAL, FOR 3-PHASE BUSBARS, CONNECTION FROM ABOVE, SIZE S00/S0



General technical data:						
product brand name		SIRIUS				
product designation		3-phase infeed terminals, size S0/S00, from above				
Size of the circuit-breaker		S00, S0				
Protection class IP / on the front		IP20				
Insulation voltage / with degree of pollution 3						
rated value	V	690				
Ambient temperature						
during storage	°C	-50 +80				
during operating	°C	-20 +60				
Installation/mounting/dimensions:						
Width	mm	44.5				
Height	mm	39				
Depth	mm	27.2				
Acceptability for application / makes the assembly of self- protected combination motor controllers (type E) according to UL 508 possible		No				
Connections:						
Design of the electrical connection						
for main current circuit		screw-type terminals				

Type of the connectable conductor cross-section	
for main contacts	
• solid	1x (2.5 16 mm²)
• stranded	1x (2,5 16 mm²)
finely stranded	
<ul> <li>with conductor end processing</li> </ul>	1x (2.5 16 mm²)
<ul> <li>for AWG conductors / for main contacts</li> </ul>	1x (10 4)

Certificates/approv	als:						
Verification of suitabil	lity			CE / UL / CSA / CCC			
General Product App	proval	Test Certificates					
(SA) CSA		Manufacturer					
Shipping Approval							
ABS	<b>ŮŇ</b> DNV	GL	Lloyd's Register	PRS	RINA		
Shipping Approval	other						
RMRS	Manufacturer	<u>other</u>					
Further information:							
Information- and Downloadcenter (Catalogs, Brochures,) http://www.siemens.com/industrial-controls/catalogs							
Industry Mall (Online ordering system) http://www.siemens.com/industrial-controls/mall							
CAx-Online-Generator http://www.siemens.com/cax							
Service&Support (Manuals, Certificates, Characteristics, FAQs,) http://support.automation.siemens.com/WW/view/en/3RV2925-5AB/all							
Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams,) http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3RV2925-5AB							





last change:

Feb 6, 2012